- Download the Nordcad smart start installer here: <u>http://downloads.nordcad.dk/smartstart/Nordcad174SmartStart_Setup.exe</u> Username: dlnordcad Password: iwantTHAThotfix
- 2. Run the downloaded setup file. If Windows protected your PC click on "More info"



3. Click on Run anyway to start the installer.



©2022 Nordcad Systems A/S

4. The installer will start to download from the internet.



5. When the download is at 100% it will start extracting the files – Please wait.

Nordcad	
Download files	
Extract files	
Install BASE	8
Install HOTFIX	
Setup CDS SITE	8
Working on files	
Extracting files	100%

6. The BASE Cadence installation will then start. This will run as administrator. Select yes to the popup.



7. Accept the license agreement and click on Next. Click on Next again.



8. Navigate to your license file you received from Nordcad by clicking on the three dots ... Find the file and click on Open.

\bigcirc Open $\leftarrow \rightarrow \checkmark \land \bigcirc$ Th	is PC → Desktop v ♂	earch Desktop	×	
Organise 👻 New folde	r			
Ouick access	Name	Date modified	Туре	
Desisten de	2c6fc914ab71.license.ORCAD.16.10.19.917.	02/09/2020 08.16	Text Docume	
 ↓ Downloads ※ ☆ Documents ※ ∞ Pictures ★ This PC Wetwork 	Vordcad174Installer	02/09/2020 07.49	Application	
	<		>	
File na	me: 2c6fc914ab71.license.ORCAD.16.10.19.917.		~	
	- Mun. M	Open	Cancel .#	
	-18-55			
			Back	instail



9. Click on Finish and the hotfix installation will then start. Select Yes to run the hotfix installation.

cādence°		_ X
Installation Summary 17.4-2019 Release		
This setup will update the installed version(17.4.0) of Cadence OrCAD and Allegro 17.4-2019 to version 17.	40.008.	
Product destination path: C:\Cadence\SPB_17.4		
Products To Install:		^
Allegro Data Manager		
Allegro Library Manager		
Allegro Library Server		
Allegro Design Authoring		
Allegro Design Authoring CIS		
Allegro Design Authoring Multi Style		
Allegro FPGA System Planner		
Allegro Library Creator		
Allegro PCB Editor Router and SI		
Allegro PCB Librarian		
Allegro PCB Router		
Backup Files	ck	Install
Instantion of the second se	tallation Help	System Requirements

- 10. Click on Install and wait for the hotfix to complete.
- 11. Click on Finish when completed.
- 12. The installer will then setup the CDS_SITE.
- 13. When the installation has been completed the screen will look like the following image.

Nordcad			_ >	
Download files				
Extract files				
Install BASE	Installation Completed			
Install HOTFIX				
Setup CDS SITE		Close		
DONE				
Creating CDSSITE			0%	

©2022 Nordcad Systems A/S

Help with OrCAD



YouTube Channel

Visit our YouTube channel, that contains a lot of different content for schematics in Capture, PCB Design and PSpice simulations. https://www.youtube.com/channel/UCes1TdH6mVgk



License Manager

-EJ0oTxAVnQ

To install the license, use the license configuration tool as shown on this link: <u>https://youtu.be/gtPHVsROW9A</u>